

BT-700PA

BETA MIXER AMPLIFIER



Description:

The BETA BT-700PA 6 Zone Mixer Amplifier with USB/SD/MP3/FM/Bluetooth, and rated power output from 700W, it is all in one solution with mixer and power amplifier into one 19" standard cabinet design, economy but of high reliable performance. It integrates different audio sources into a mixer amplifier: mic 1-3 (6.5mm) and 1-2 AUX/3 line input. One USB and one SD slots on front provide easy access and operation for installer and end-user. The amplifier is design with complete protection of overload, short circuit, CC failures and high temp to avoid any damage, allowing for 24/7/365 long time use. These amplifiers are suitable for applications in bank, mosque, school, hotel, restaurant, theme centers and shopping center.

Features:

- Public address (PA) 6 zone mixer power amplifier
- 19" rack mount amplifier
- Rated output 700W
- 6 zone speaker outputs to 100V/70V 4-16 Ω
- 6 zone speaker outputs with independent volume control and chime button
- Built-in digital screen display with SD/USB/MP3/FM tuner/Bluetooth
- Mic1-3 input 6.5mm jack
- AUX RCA 1-2 and line 3 input
- Volume control for Mic1-3 and AUX RCA 1-2, chime button and 6 zone volume control
- Visual indicators include AC and DC Power, protection, clip, 6 zone status and output level meters
- Complete amplifier protection includes overload, clip, short circuit and high temp protection
- 220-240V , 50/60Hz

TECHNICAL SPECIFICATIONS

Model	BT-700PA
Type	AB Class
Description	6 Zone Mixer Amplifier with USB/SD/MP3/FM/Bluetooth
Power Output	Rated output 700W (RMS 650W)
Speaker Output	70/100V at 4-16 Ω
Input	Mic1-3 input 6.5mm jack, AUX RCA 1-2 and line 3 input
Front panel	6 speaker control switches
Rear panel	6 independent speaker outputs with screw connector
Frequency Response	80Hz-18kHz
Total harmonic distortion	<1% to 1/3 rated power
Independent volume adjustment	6
Protection	High temp, short circuit, overhead & overload, cc failures
Heat dissipation	Side-in and back-out forced fan cooling
Power Supply	220-240V , 50/60Hz
Power Consumption	390W
Dimension	484×353×88mm
Weight	9.8k

www.betaaudio.org