



BT-350PA AMPLIFIER



Description

The BT-350PA from Beta Audio is a switched power amplifier, ideal for fixed installations, it has two 250W RMS channels, with 4Ω and 70V/100V outputs. Great power supply, super ring and high efficiency transformer, protected against surges, short circuits and overheating.

Technical specifications

Model	BT-350PA
Type	Two channel amplifier
Power	350W(peak) x 2 - 250W(RMS) x 2
Frequency response	20Hz - 20kHz
Input impedance	20 k Ω
Limit input level	20dBv \pm 1.5 dBv
Input voltages	0.775V, 1V, 14V (selection switch)
Output	4 Ω , 70V/100V
Signal/noise ratio	>95dB (ref. 1kHz, weighted A)
Total harmonic distortion (THD)	<0.1%
Protection	Electronic protection circuit for temperature, overload, short circuit
Voltage	220/240V AC 50-60Hz
Consumption	500W
Form factor	2U rack 19"
Dimensions	480 x 350 x 88 mm
Weight	14 Kg.

